

## **Karts Headlight Fix**

**The Karts have experienced dim headlights. We have determined that the manufacture wired the lights improperly. Below is the repair for the Headlight Circuit.**

1. Locate the Headlight switch.
2. Remove the Yellow wire from the switch. This is the power wire for the headlight switch.
3. Cut yellow wire at the harness and tape up harness.
4. Locate the horn switch.
5. There are two wires that feed the switch and go to a 2 pin connector. Locate the red wire. This is the power for the horn switch. The red wire is protected by the fuse located in the fuse panel.
6. Take the 2 inch piece of yellow wire that you cut from the headlight switch and splice it to the red wire of the horn switch.
7. Connect the yellow wire to headlight switch.
8. Turn on the headlight switch and the lights should work.